

## SILICON MICROWAVE POWER TRANSISTOR

### PRODUCT DATA SHEET

#### FEATURES:

- High Output Power  
6 Watts @ 2.3 GHz
- High Gain Bandwidth Product  
 $f_t = 6.0 \text{ GHz @ } I_C = 1.08 \text{ A}$
- High Gain  
 $|S_{21}|^2 = 9.0 \text{ dB @ } 2.3 \text{ GHz}$



#### DESCRIPTION AND APPLICATIONS:

Bipolarics' BPT23E06S is a high performance silicon bipolar transistor intended for linear power applications at UHF frequencies to 6.0 GHz. Typical applications include amplifiers in aeronautical, maritime and personal communication applications. The BPT23E06S is bonded common emitter for linear applications. Linear output power of 6 Watts can be achieved. Stud Mount package makes this device excellent for industrial and military products. Uniformity and reliability are assured by the use of ion implanted junctions, ion implanted ballast resistors and gold metallization.

- Stud Mount Package (Package 28S)

#### PERFORMANCE DATA:

- Electrical Characteristics ( $T_A = 25^\circ\text{C}$ )

#### Absolute Maximum Ratings:

SYMBOL	PARAMETERS	RATING	UNITS
$V_{CBO}$	Collector-Base Voltage	40	V
$V_{CEO}$	Collector-Emitter Voltage	20	V
$V_{EBO}$	Emitter-Base Voltage	3.0	V
$I_C$	Collector Current (instantaneous)	2.16	A
$T_J$ (1)	Junction Temperature	200	$^\circ\text{C}$
$T_{STG}$	Storage Temperature	-65 to 150	$^\circ\text{C}$

(1) Depends on package

SYMBOL	PARAMETERS & CONDITIONS $V_{CE} = 15\text{V}, I_C = 1.08 \text{ A}, \text{ Class A, unless stated}$	UNIT	MIN.	TYP.	MAX.
$P_{1dB}$	Power output at 1 dB compression: $f = 2.3 \text{ GHz}$	W		6.0	
$G_{1dB}$	Gain at 1dB compression: $f = 2.3 \text{ GHz}$	dB		8.0	
$\eta$	Collector Efficiency Class A	%		30	
$C_{CB}$	Collector Base Capacitance: $f = 1 \text{ MHz}, I_E = 0$	pF		10.0	
$h_{FE}$	Forward Current Transfer Ratio: $V_{CE} = 8\text{V}, I_C = 500 \text{ mA}$		20	60	100
$P_T$	Total Power Dissipation ( $T_C = 25^\circ\text{C}$ )	W		15.0	